


## Dual PNP Small Signal Transistor



### Features

- Epoxy meets UL-94 V-0 flammability rating
- Surface mount package ideally Suited for Automatic Insertion
- Reduces number of components and board space
- Part no. with suffix "Q" means AEC-Q101 qualified


### Application

- Ideal for low power amplification and switching

### Mechanical Data

- **Package:** SOT-363
- **Terminals:** Tin plated leads, solderable per J-STD-002 and JESD22-B102
- **Marking:** K2F

### Equivalent circuit



### ■Maximum Ratings (Ta=25°C Unless otherwise specified)

Item	Symbol	Unit	Value
Collector-Base Voltage	$V_{CBO}$	V	-60
Collector-Emitter Voltage	$V_{CEO}$	V	-60
Emitter-Base Voltage	$V_{EBO}$	V	-5
Collector Current -Continuous	$I_C$	mA	-600
Total Device Dissipation (*)	$P_D$	mW	200
Thermal Resistance Junction to Ambient (*)	$R_{thJA}$	K/W	625
Junction Temperature	$T_J$	°C	150
Storage Temperature	$T_{STG}$	°C	-55 to +150

(\*) Device mounted on FR-4 PCB 1.0 x 1.0 x 0.06 inch



# MMDT2907AQ

## ■ Electrical Characteristics (Ta=25°C unless otherwise specified)

Item	Symbol	Unit	Conditions	Min	TYP	Max
Collector-base breakdown voltage	$V_{CBO}$	V	$I_C=-10\mu A, I_E=0$	-60		
Collector-emitter breakdown voltage	$V_{CEO}$	V	$I_C=-10mA, I_B=0$	-60		
Emitter-base breakdown voltage	$V_{EBO}$	V	$I_E=-10\mu A, I_C=0$	-5		
Collector cut-off current	$I_{CBO}$	nA	$V_{CB}=-50V, I_E=0$			-20
Collector cut-off current	$I_{CEX}$	nA	$V_{CE}=-30V, V_{EB(off)}=-0.5V$			-50
Emmitter cut-off current	$I_{EBO}$	nA	$V_{EB}=-5V, I_C=0$			-20
DC current gain	$h_{FE1}$		$V_{CE}=-10V, I_C=-0.1mA$	75		
	$h_{FE2}$		$V_{CE}=-10V, I_C=-1mA$	100		
	$h_{FE3}$		$V_{CE}=-10V, I_C=-10mA$	100		
	$h_{FE4}$		$V_{CE}=-10V, I_C=-150mA$	100		300
	$h_{FE5}$		$V_{CE}=-10V, I_C=-500mA$	50		
Collector-emitter saturation voltage	$V_{CE(sat)}$	V	$I_C=-150mA, I_B=-15mA$			-0.4
Collector-emitter saturation voltage	$V_{CE(sat)}$	V	$I_C=-500mA, I_B=-50mA$			-1.6
Base-emitter saturation voltage	$V_{BE(sat)}$	V	$I_C=-150mA, I_B=-15mA$			-1.3
Base-emitter saturation voltage	$V_{BE(sat)}$	V	$I_C=-500mA, I_B=-50mA$			-2.6
Transition frequency	$f_T$	MHz	$V_{CE}=-20V, I_C=-50mA, f=100MHz$	200		
Delay time	$t_d$	ns	$V_{CC}=-30V,$ $I_C=-150mA, I_{B1}=-15mA$			10
Rise time	$t_r$	ns				40
Storage time	$t_s$	ns	$V_{CC}=-6V,$ $I_C=-150mA, I_{B1}=-I_{B2}=-15mA$			225
Fall time	$t_f$	ns				60

## ■ Ordering Information (Example)

PREFERRED P/N	PACKING CODE	UNIT WEIGHT(g)	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
MMDT2907AQ	F2	Approximate 0.009g	3000	30000	120000	7" reel



## ■ Characteristics (Typical)

Fig.1 - Static characteristic




Fig.2 - DC Current Gain




Fig.3 - Collect-Emmitter Saturation Voltage




Fig.4 - Base-Emmitter Voltage




Fig.5 - Base-Emmitter On Voltage









Fig.6 - Cob/Cib—VCB/VEB





# MMDT2907AQ

## ■SOT-363 Package Outline Dimensions & Soldering Footprint



UNIT: mm

SYMBOL	DIMENSIONS			
	INCHES		Millimeter	
	MIN.	MAX.	MIN.	MAX.
A	0.035	0.043	0.900	1.100
A1	0.000	0.004	0.000	0.100
A2	0.035	0.039	0.900	1.000
b	0.006	0.014	0.150	0.350
c	0.004	0.010	0.100	0.250
D	0.071	0.087	1.800	2.200
E	0.045	0.053	1.150	1.350
E1	0.085	0.096	2.150	2.450
e	0.026TYP		0.650TYP	
e1	0.047	0.055	1.200	1.400
L	0.021REF		0.525REF	
L1	0.010	0.018	0.260	0.460
theta	0°	8°	0°	8°

**NOTE:**

1. PACKAGE BODY SIZES EXCLUDE MOLD FLASH AND GATE BURRS.
2. TOLERANCE 0.1mm UNLESS OTHERWISE SPECIFIED.
3. THE PAD LAYOUT IS FOR REFERENCE PURPOSES ONLY.



## MMDT2907AQ

---

### Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with automotive electronics, are not designed for use in medical, life-saving, lifesustaining, or military, Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.